



PATENT APPLICATION

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re the Application of:

Theodore BUOT

Group Art Unit: 2681

Application No.: 10/701,072

Examiner: Not yet assigned

Confirmation No.: 6302

Filed: November 5, 2003

Attorney Dkt. No.: 60091.00262

For: DATA TRANSMISSION METHOD AND SYSTEM

CLAIM FOR PRIORITY UNDER 35 USC § 119

Commissioner for Patents
P.O. Box 1450
Alexandria, VA 22313-1450

April 5, 2004

Sir:

The benefit of the filing dates of the following prior foreign application filed in the following foreign country is hereby requested for the above-identified patent application and the priority provided in 35 U.S.C. §119 is hereby claimed:


**Finnish Patent Application No. PCT/FI02/00870 filed on November 7, 2002 in
Finland**

In support of this claim, certified copy of said original foreign application is filed herewith.

It is requested that the file of this application be marked to indicate that the requirements of 35 U.S.C. §119 have been fulfilled and that the Patent and Trademark Office kindly acknowledge receipt of this document.

Please charge any fee deficiency or credit any overpayment with respect to this paper to Counsel's Deposit Account No. 50-2222.

Respectfully submitted,



Douglas H. Goldhush
Registration No. 33,125

Customer No. 32294
SQUIRE, SANDERS & DEMPSEY LLP
14TH Floor
8000 Towers Crescent Drive
Tysons Corner, Virginia 22182-2700
Telephone: 703-720-7800
Fax: 703-720-7802

DHG:kbd

Enclosure: Priority Document (1)

PATENTTI- JA REKISTERIHALLITUS
NATIONAL BOARD OF PATENTS AND REGISTRATION

Helsinki 27.10.2003

ETUOIKEUSTODISTUS
PRIORITY DOCUMENT



Hakija
Applicant

1. Nokia orporation, Helsinki, FI
2. Buot, Theodore, Spanish Village, SG

Kansainvälinen patenttihakemus nro
International patent application no PCT/FI02/00870

Kansainvälinen tekemispäivä
International filing date 07.11.2002

Keksinnön nimitys
Title of invention

"Data transmission method and system"

Täten todistetaan, että oheiset asiakirjat ovat tarkkoja jäljennöksiä kansainvälisiä patenttihakemuksia vastaanottavana viranomaisena toimivalle Patentti- ja rekisterihallitukselle alkuaan annetuista anomuslomakkeesta, selityksestä, patenttivaatimuksista, tiivistelmästä ja piirustuksista sekä niihin tehdyistä korjauksista.

This is to certify that the annexed documents are true copies of the request form, description, claims, abstract and drawings, originally filed with the Finnish Patent Office acting as receiving Office for the international patent applications, and of any corrections thereto.


Pirjo Kalla
Tutkimussihteeri

Maksu 50 €
Fee 50 €

Maksu perustuu kauppa- ja teollisuusministeriön antamaan asetukseen 1027/2001 Patentti- ja rekisterihallituksen maksullisista suoritteista muutoksineen.

The fee is based on the Decree with amendments of the Ministry of Trade and Industry No. 1027/2001 concerning the chargeable services of the National Board of Patents and Registration of Finland.

Osoite: Arkadiankatu 6 A
Address: P.O.Box 1160
FIN-00101 Helsinki, FINLAND

Puhelin: 09 6939 500
Telephone: + 358 9 6939 500

Telefax: 09 6939 5328
Telefax: + 358 9 6939 5328

HOME COPY

1/5

PCT REQUEST

2021243PC/nu

Original (for SUBMISSION) - printed on 07.11.2002 11:18:03 AM

0	For receiving Office use only	
0-1	International Application No.	PCT/FI02/00870
0-2	International Filing Date	07 NOV 2002 (07.11.02)
0-3	Name of receiving Office and "PCT International Application"	The Finnish Patent Office PCT International Application
0-4	Form - PCT/RO/101 PCT Request	
0-4-1	Prepared using	PCT-EASY Version 2.92 (updated 01.10.2002)
0-5	Petition The undersigned requests that the present international application be processed according to the Patent Cooperation Treaty	
0-6	Receiving Office (specified by the applicant)	National Board of Patents and Registration (Finland) (RO/FI)
0-7	Applicant's or agent's file reference	2021243PC/nu
I	Title of invention	DATA TRANSMISSION METHOD AND SYSTEM
II	Applicant	
II-1	This person is:	applicant only
II-2	Applicant for	all designated States except US
II-4	Name	NOKIA CORPORATION
II-5	Address:	Keilalahdentie 4 FIN-02150 Espoo Finland
II-6	State of nationality	FI
II-7	State of residence	FI
III-1	Applicant and/or inventor	
III-1-1	This person is:	applicant and inventor
III-1-2	Applicant for	US only
III-1-4	Name (LAST, First)	BUOT, Theodore
III-1-5	Address:	Apt 62, Farrer Road #02-03, Spanish Village 268847 Singapore Singapore
III-1-6	State of nationality	PH
III-1-7	State of residence	SG

PCT REQUEST

2021243PC/nu

Original (for SUBMISSION) - printed on 07.11.2002 11:18:03 AM

IV-1	Agent or common representative; or address for correspondence The person identified below is hereby/has been appointed to act on behalf of the applicant(s) before the competent International Authorities as:	agent
IV-1-1	Name	KOLSTER OY AB
IV-1-2	Address:	Iso Roobertinkatu 23 P.O. Box 148 FIN-00121 Helsinki Finland
IV-1-3	Telephone No.	+ 358 9 618 821
IV-1-4	Facsimile No.	+ 358 9 602 244
IV-1-5	e-mail	kolster@kolster.fi
V	Designation of States	
V-1	Regional Patent (other kinds of protection or treatment, if any, are specified between parentheses after the designation(s) concerned)	AP: GH GM KE LS MW MZ SD SL SZ TZ UG ZM ZW and any other State which is a Contracting State of the Harare Protocol and of the PCT EA: AM AZ BY KG KZ MD RU TJ TM and any other State which is a Contracting State of the Eurasian Patent Convention and of the PCT EP: AT BE BG CH&LI CY CZ DE DK EE ES FI FR GB GR IE IT LU MC NL PT SE SK TR and any other State which is a Contracting State of the European Patent Convention and of the PCT OA: BF BJ CF CG CI CM GA GN GQ GW ML MR NE SN TD TG and any other State which is a member State of OAPI and a Contracting State of the PCT
V-2	National Patent (other kinds of protection or treatment, if any, are specified between parentheses after the designation(s) concerned)	AE AG AL AM AT (patent and utility model) AU AZ BA BB BG BR BY BZ CA CH&LI CN CO CR CU CZ (patent and utility model) DE (patent and utility model) DK (patent and utility model) DM DZ EC EE (patent and utility model) ES FI (patent and utility model) GB GD GE GH GM HR HU ID IL IN IS JP KE KG KP KR KZ LC LK LR LS LT LU LV MA MD MG MK MN MW MX MZ NO NZ OM PH PL PT RO RU SC SD SE SG SI SK (patent and utility model) SL TJ TM TN TR TT TZ UA UG US UZ VC VN YU ZA ZM ZW

PCT REQUEST

2021243PC/nu

Original (for SUBMISSION) - printed on 07.11.2002 11:18:03 AM

V-5	Precautionary Designation Statement In addition to the designations made under items V-1, V-2 and V-3, the applicant also makes under Rule 4.9(b) all designations which would be permitted under the PCT except any designation(s) of the State(s) indicated under item V-6 below. The applicant declares that those additional designations are subject to confirmation and that any designation which is not confirmed before the expiration of 15 months from the priority date is to be regarded as withdrawn by the applicant at the expiration of that time limit.		
V-6	Exclusion(s) from precautionary designations	NONE	
VI	Priority claim	NONE	
VII-1	International Searching Authority Chosen	Swedish Patent Office (ISA/SE)	
VIII	Declarations	Number of declarations	
VIII-1	Declaration as to the identity of the inventor	-	
VIII-2	Declaration as to the applicant's entitlement, as at the international filing date, to apply for and be granted a patent	1	
VIII-3	Declaration as to the applicant's entitlement, as at the international filing date, to claim the priority of the earlier application	-	
VIII-4	Declaration of inventorship (only for the purposes of the designation of the United States of America)	-	
VIII-5	Declaration as to non-prejudicial disclosures or exceptions to lack of novelty	-	

PCT REQUEST

2021243PC/nu


Original (for SUBMISSION) - printed on 07.11.2002 11:18:03 AM

VIII-2-1	Declaration: Entitlement to apply for and be granted a patent Declaration as to the applicant's entitlement, as at the international filing date, to apply for and be granted a patent (Rules 4.17(ii) and 51bis.1(a)(ii)), in a case where the declaration under Rule 4.17(iv) is not appropriate: Name:	in relation to this international application NOKIA CORPORATION is entitled to apply for and be granted a patent by virtue of the following:
VIII-2-1 (ii)		NOKIA CORPORATION is entitled as employer of the inventor, BUOT, Theodore
VIII-2-1 (ix)	This declaration is made for the purposes of:	all designations except the designation of the United States of America.

PCT REQUEST

2021243PC/nu

Original (for SUBMISSION) - printed on 07.11.2002 11:18:03 AM

IX	Check list	number of sheets	electronic file(s) attached
IX-1	Request (including declaration sheets)	5	-
IX-2	Description	14	-
IX-3	Claims	3	-
IX-4	Abstract	1	EZABST00.TXT
IX-5	Drawings	4	-
IX-7	TOTAL	27	
	Accompanying items	paper document(s) attached	electronic file(s) attached
IX-8	Fee calculation sheet	✓	-
IX-9	Original separate power of attorney	✓	-
IX-11	Copy of general power of attorney	✓	-
IX-17	PCT-EASY diskette	-	Diskette
IX-19	Figure of the drawings which should accompany the abstract	5	
IX-20	Language of filing of the international application	English	
X-1	Signature of applicant, agent or common representative	 Tapio Valkeiskangas	
X-1-1	Name	KOLSTER OY AB	

FOR RECEIVING OFFICE USE ONLY

10-1	Date of actual receipt of the purported international application	07 NOV 2002 (07.11.02)
10-2	Drawings:	
10-2-1	Received	
10-2-2	Not received	
10-3	Corrected date of actual receipt due to later but timely received papers or drawings completing the purported international application	
10-4	Date of timely receipt of the required corrections under PCT Article 11(2)	
10-5	International Searching Authority	ISA/SE
10-6	Transmittal of search copy delayed until search fee is paid	

FOR INTERNATIONAL BUREAU USE ONLY

11-1	Date of receipt of the record copy by the International Bureau	
------	--	--

Data Transmission Method and System

Field

The invention relates to a data transmission method and system in a radio telecommunication system.

5 Background

In Code Division Multiple Access systems (CDMA), several users share the same frequency. Different users are separated from each other by codes. The use of the same frequency causes interference to other cells. The transmit power control is the most important parameter used to limit the interference, because the higher the power, the more interference. This is why the power control is the key issue especially in the CDMA systems.

There are, however, many problems in the power control. For instance, the calculation of the load factor or of the capacity utilisation need the estimation of the interference caused by other cells. The interference originating from neighbouring cells can be even 40 percent of the total interference in the cell. Attention also had to be paid to the fact that the downlink interference varies for every user of the cell mainly due to the variation of locations. Another fact which has to be taken into consideration is that the user equipment only knows the total interference. All these matters make the power control estimation and thereby power restriction difficult in the CDMA systems especially in multi-cell environments.

Brief description of the invention

It is an object of the invention to provide an improved method for allocating resources for users in a cellular radio system using the code division multiple access. This is achieved by a data transmission method in a radio telecommunication system, comprising setting a maximum value for cell power, determining a bit rate increase in a cell on the basis of capacity requests, estimating the increase of the transmission power in a cell caused by the capacity increase, determining the cell power on the basis of the current cell power and the estimated power increase, estimating the increase of the transmission power needed in the neighbouring cells caused by the capacity growth in the current cell, if the cell power of any of the neighbouring cells exceeds the maximum value, limiting the resource allocation in the cell requesting capacity.

The invention also relates to a data transmission method in a cellular telecommunication system, comprising setting a maximum value for a cell power, determining bit rate increases in cells on the basis of capacity requests, evaluating the costs of the additional loads due to the capacity requests, estimating the increase of the transmission power in the current cell caused by the capacity growth, determining the cell power of the current cell on the basis of the current cell power and the estimated power increase, estimating the increase of the transmission power needed in the neighbouring cells caused by the capacity growth in the current cell, allocating resources in a growing order of the costs, if the cell power of any of the neighbouring cells exceeds the maximum value, limiting the resource allocation in the cell requesting capacity.

The invention also relates to a radio telecommunication system comprising means for determining a bit rate increase in a cell on the basis of capacity requests, means for estimating the increase of transmission power caused by the capacity increase, means for determining the cell power on the basis of the current cell power and the estimated power increase, means for estimating the increase of the transmission power needed in the neighbouring cells caused by the capacity growth in the current cell, means for limiting the resource allocation in the cell requesting capacity.

The invention also relates to a radio telecommunication system comprising means for determining a bit rate increase in a cell on the basis of capacity requests, means for evaluating the cost of an additional load, means for allocating resources in a growing order of costs, means for estimating the increase of transmission power caused by the capacity increase, means for determining the cell power on the basis of the current cell power and the estimated power increase, means for estimating the increase of the transmission power needed in the neighbouring cells caused by the capacity growth in the current cell, means for limiting the resource allocation in the cell requesting capacity.

Preferred embodiments of the invention are described in the dependent claims.

The method and system of the invention provide several advantages. In a preferred embodiment of the invention, it is possible to control the transmission power of each cell or sector in order to avoid the exceeding of the given maximum value.

List of the drawings

In the following, the invention will be described in greater detail with reference to the preferred embodiments and the accompanying drawings, in which

- 5 Figure 1 shows an example of a CDMA-system,
 Figure 2 shows an example of a cellular network,
 Figure 3 is a flow chart,
 Figure 4 is another flow chart and
 Figure 5 illustrates an example of a radio network controller.

10 Description of the embodiments

 With reference to Figure 1, examine an example of a data transmission system in which the preferred embodiments of the invention can be applied. The invention can be implemented in the RNC (Radio Network Controller) and/or BS (Base Station) and can e.g. be a part of RAN (Radio Access
15 Network) for instance UTRAN (UMTS Terrestrial Radio Access Network) solution as well as IPRAN (Internet Protocol RAN).

 In Figure 1 the embodiments are described in a simplified radio system, which represents a Code Division Multiple Access, CDMA, system. The Code Division Multiple Access technique is used nowadays for example in radio systems which are known at least by the names IMT-2000 (International
20 Mobile Telecommunications 2000) and UMTS (Universal Mobile Telecommunications System). The embodiments are not, however, restricted to these systems given as examples but a person skilled in the art may apply the solution in other radio systems provided with the necessary properties.

25 Figure 1 is a simplified block diagram, which describes the most important network elements of the radio system and the interfaces between them. The structure and function of the network elements are not described in detail because they are generally known.

 The main parts of the radio system are a core network (CN) 100, a
30 radio access network 130 and user equipment (UE) 170. The term UTRAN is an abbreviation from UMTS Terrestrial Radio Access Network, i.e. the radio access network belongs to the third generation and is implemented by wide-band code division multiple access WCDMA. Generally, the radio system can also be defined as follows: the radio system consists of a user terminal, which
35 is also called a subscriber terminal or a mobile station, and of a network part,

which includes the fixed infrastructure of the radio system, i.e. a core network, a radio access network and a base station system.

A mobile services switching centre (MSC) 102 is the centre of the circuit-switched side of the core network 100. The mobile services switching centre 102 is used to serve the connections of the radio access network 130. The tasks of the mobile services switching centre 102 typically include switching, paging, user terminal location registration, handover management, collection of subscriber billing information, data encryption parameter management, frequency allocation management and echo cancellation.

The number of mobile services switching centres 102 may vary: a small network operator may have only one mobile services switching centre 102, whereas large core networks 100 may have several ones. Figure 1 shows another mobile services switching centre 106 but its connections to other network elements are not illustrated to keep Figure 1 sufficiently clear.

Large core networks 100 may comprise a separate gateway mobile services switching centre (GMSC) 110, which is responsible for circuit-switched connections between the core network 100 and the external networks 180. The gateway mobile services switching centre 110 is located between the mobile services switching centres 102, 106 and the external networks 180. The external network 180 may be, for example, a public land mobile network PLMN or a public switched telephone network PSTN.

The core network 100 typically comprises other parts, too, such as a home location register HLR, which includes a permanent subscriber register and, if the radio system supports the GPRS, a PDP address (PDP = Packet Data Protocol), and a visitor location register VLR, which includes information on roaming of the user terminals 170 in the area of the mobile services switching centre 102. Not all the parts of the core network are shown in Figure 1 to keep it clear.

A serving GPRS support node (SGSN) 118 is the centre of the packet-switched side of the core network 100. The main task of the serving GPRS support node 118 is to transmit and receive packets with the user terminal 170 supporting packet-switched transmission, utilizing the radio access network 130. The serving GPRS support node 118 includes user information and location information on the user terminal 170.

A gateway GPRS support node (GGSN) 120 on the packet-switched side corresponds to the gateway mobile services switching centre 110 of the

circuit-switched side, with the exception that the gateway GPRS support node 120 has to be able to route outgoing traffic from the core network 100 to external networks 182, whereas the gateway mobile services switching centre 110 routes only the incoming traffic. In the example, the external networks 182 are represented by the Internet, via which a considerable part of wireless telephone traffic can be transmitted in the future.

The radio access network 130 consists of radio network subsystems 140, 150. Each radio network subsystem 140, 150 consists of radio network controllers (RNC) 146, 156 and B nodes 142, 144, 152, 154. The B node is rather an abstract concept, which is frequently replaced by the term 'base station'.

The radio network controller 146, 156 is usually responsible for the following tasks, for example: management of the radio resources of the base transceiver station or B-node 142, 144, 152, 154, intercell handover, measurement of time delays on the uplink, implementation of the operation and management interface, and management of power control.

The radio network controller 146, 156 includes at least one transceiver. One radio network controller 146, 156 may serve one cell or several sectorized cells. The cell diameter may vary from a few metres to dozens of kilometres. The radio network controller 146, 156 is often deemed to include a transcoder, too, for performing conversion between the speech coding format used in the radio system and the speech coding format used in the public switched telephone system. In practice the transcoder, however, is usually located in the mobile services switching centre 102. The radio network controller 146, 156 is usually responsible for the following tasks, for example: measurements on the uplink, channel coding, encryption and scrambling coding.

The user terminal 170 consists of two parts: mobile equipment (ME) 172 and a UMTS subscriber identity module (USIM) 174. The user terminal 170 comprises at least one transceiver for establishing a radio connection to the radio access network 130. The user terminal 170 may include at least two different subscriber identity modules. In addition, the user terminal 170 comprises an antenna, a user interface and a battery. Nowadays various kinds of user terminals 170 are available, e.g. terminals that are installed in a car and portable terminals. The user terminals 170 also have properties similar to those of a personal computer or a portable computer.

The USIM 174 includes information on the user and information on data security, e.g. an encryption algorithm, in particular.

It is obvious to a person skilled in the art that the interfaces included in the radio telecommunications system are determined by the hardware implementation and the standard used, for which reason the interfaces of the system may differ from those shown in Figure 1. In the UMTS, the most important interfaces are the lu interface between the core network and the radio access network, which is divided into the luCS (CS = Circuit Switched) interface of the circuit-switched side and the luPS (PS = Packet Switched) interface of the packet-switched side, and the Uu interface between the radio access network and the user terminal. The interface defines what kind of messages different network elements may use to communicate with one another. The object of the standardisation of interfaces is to enable function between network elements of different producers. In practice, however, some of the interfaces are producer-specific.

Figure 2 illustrates a simplified example of a cellular network. In the CDMA systems the same frequency is shared between several users separated by different codes. The same frequency is typically used in several cells, too. The result of the sharing the same frequency is that other cells and cross-talking cause quite a lot of interference to each user. Thus an efficient power control is one of the main problems in the CDMA systems. The transmission power of each user has to be restricted to be as low as possible in the limits of the acceptable error rate.

In the example of the Figure 2, there are two cells 200, 202. Both of the base stations 142, 144 use the same carrier frequency. There are several user terminals 170A-E in the two cells. The user terminals cause interference to each other, because the codes used to separate them, often called channelisation codes, are not totally uncorrelated to each other. In adjusting the transmission power one also has to pay attention to the fact that the nearer the cell edge the mobile is, the more the transmitted signal attenuates.

Figure 3 is a flowchart describing an embodiment of a data transmission method, which suits especially the circumstances described with the aid of the example of Figure 2. The method is related to the admission control and load control procedures. The principle of the admission control is to check that the admittance of the new connection will not restrict the planned coverage area or make the quality of existing connection worse. The main target of

the load control is to ensure that the system is not overloaded and remains stable. In this application, the term cell is used to mean both a radio cell and a sector.

In the method, terminals measure one or more values which describe the level or the quality of the neighbouring cells pilots. These measurements can be utilized in the interference estimation. The radio network controller typically has information on the transmission powers of all the cells. It also has information on the quality of the pilot signals of all the cells, often called as CPICHE_d/I₀, that is to say Common Pilot Channel energy-to-noise-density, which are measured by terminals and reported periodically to radio network controllers. The terminals carry out these measurements particularly when they are about to perform a soft handover. The terminals report the neighbouring cell measurements to the radio network controller. These measurements can be, for instance, above-mentioned energy-to-noise-density ratio (E_d/I₀) measurements. Thus the radio network controller knows the total power in every cell.

In addition, it should be noticed that resource management, in other words resource allocations and releases, is the usual task of the radio network controller.

The embodiment of the method starts from block 300. The method is especially beneficial in clarifying the influence of the expected power increase in one cell on the other cells. In block 302 a maximum value is set for cell power in each cell is set. The maximum value is preferably based on the limit for allowable interference caused by the cell for the other cells. Thus the maximum values can differ, for instance, in the function of time or they can be different for every cell. The adaptation of the method does not restrict the selection of the maximum values. If the cells are of the same size, the maximum values are typically set to be the same for all of the cells. With the aid of the method, the transmission powers can be controlled to be under the set limits or at least near them.

In block 304, a bit rate increase in a cell is determined. The current power and bit rates used are known, and the increase is determined on the basis of the capacity requests. The capacity is needed for sending speech, packet data, picture etc. The increase of the bit rate depends on the amount of the requested connections as well as on their type; speech needs a lower bit rate than a picture, for example.

In block 306, the increase of the transmission power in a cell caused by the capacity increase is estimated; the bit rate increase causes, of course, a power increase. The power increase is preferably determined by using a derivative method, an integral method or both. By using the derivative method,
 5 the power increase is determined

$$\Delta P_s = \frac{\Delta L}{1 - (LF)} \cdot P_s \quad (1)$$

where

ΔP_s = increase of the transmission power of the cell,

10 ΔL = increase of the load of the cell,

P_s = the current transmission power of the cell

LF = a load factor, which can be determined as an average of E_b/N_0 , which is typically replaceable with the measured signal-to-noise ratio.

15 By using the integral method, the power increase is determined

$$\Delta P_s = \frac{\Delta L}{1 - (LF) - \Delta L} \cdot P_s, \quad (2)$$

where

ΔP_s = increase of the transmission power of the cell,

20 ΔL = increase of the load of the cell,

P_s = the current transmission power of the cell,

LF = a load factor, which can be determined as an average of E_b/N_0 , which is typically similar to the measured signal-to-noise ratio.

25 In block 308, the cell power is determined on the basis of the current cell power and the estimated power increase. This is done preferably by adding the estimated power increase to the known current power.

In block 310, the increase of the transmission power needed in the other, typically neighbouring cells due to the capacity increase is estimated.

30 The total power of a cell is determined with the aid of estimating the current cell interference and the interference caused by other cells, thus adjacent cells affect considerably to each other's interference level. The location of a user affects the interference: if the user is near the cell edge, the interference from the neighbouring cell is stronger than if the user were far from the edge.

The amount of the interference affecting mobile u in cell j , that is to say the cell of interest, originating from another cell k can be expressed in relation to the current cell interference (the interference originating from the cell j) as follows

5

$$f_i(u, k) = \frac{P_s(k)\gamma(u, k)}{[P_s(j) - P_{DL}(u, j)](1 - \alpha)\gamma(u, j)}, \quad (3)$$

where

u is a user number,

j is a cell of interest,

10

$P_s(k)$ is the transmission power of cell k ,

$\gamma(u, k)$ is the propagation attenuation between the user and cell k ,

γ is a factor, which is typically equivalent to $E_d/I_o(u, k)$ multiplied by a selected constant. The $E_d/I_o(u, k)$ values are available in the radio network controller due to the mobile measurements,

15

α is the downlink orthogonality of the current cell interference,

$P_{DL}(u, j)$ is the downlink power allocated to user u at cell j ,

k is a chosen cell, typically an adjacent cell.

If the proportion of interference to every user in cell j originating from cell k is known, then the ratio of interference from cell k into the cell j is

20

$$F(k) = \frac{\sum_u f_i(u, k) P_{DL}(u, k)}{P_s(j)}, \quad (4)$$

where

f_i is the amount of the interference affecting to mobile u in cell j originating in another cell k related to the current cell interference,

25

u is a user number,

j is a cell of interest,

$P_s(k)$ is the transmission power of cell j ,

$P_{DL}(u, j)$ is the downlink power allocated to user u at cell k ,

30

k is a chosen cell, typically an adjacent cell.

The transmission power in cell j is naturally proportional to the total interference in cell j and is derived from the downlink load curve. The power can thus be expressed as follows

$$P_s(j) = C \cdot [I(j) + I(k) + I(l) + \dots], \quad (5)$$

where

C is a predetermined constant typically used as a scaling factor,

I(j) is an interference originating from cell j (the cell of interest),

I(k), I(l) etc. are interferences originating from the other cells.

The terms I(k), I(l) etc. can be replaced by the interference factors F(k), F(l) etc. The interference factors representing the interference affecting to mobile u in cell j originating in other cells are denoted as related to the current cell interference in the formula (4). Thus the power can be expressed as follows

$$P_s(j) = C \cdot I(j) [1 + F_{tot}], \quad (6)$$

where

C is a predetermined constant typically used as a scaling factor,

I(j) is an interference originating from cell j (the cell of interest),

F_{tot} is the total interference coming from other cells into cell j.

The increase of power in cell j caused by the increase of the transmission power in cell k is calculated by the formula

$$P_s'(j) = P_s(j) (1 + F_{tot}') / (1 + F_{tot}), \quad (7)$$

where

P_s(j) is the power before the increase, called in this application current power,

F_{tot}' is the total interference factor due to the power increase,

F_{tot} is the interference factor before the power increase (that is to say due to the current power).

The change of the interference in cell j caused by the increase of the transmission power in cell k is determined

$$\Delta F(k) = (I + F_{tot}) \cdot \Delta P_s(k) / P_s(k), \quad (8)$$

where

F_{tot} is the same as in the equations (5) and (6),

ΔP_s(k) is the increase of the transmission power in cell k,

$P_s(k)$ is the current transmission power in cell k .

If the cell power of any of the neighbouring cells exceeds the maximum value, then the resource allocation in the cell requesting capacity is limited in order to avoid the interference level exceeding the boundary of the interference tolerance of the system in block 312. The resource allocation can be restricted by offering lower bit rates or by limiting the number of new users.

The method can be repeated till there is no longer a cell which exceeds the upper limit of the maximum power. Pointer 316 represents this repeating process. The method ends in block 314.

Figure 4 is a flowchart describing another embodiment of the data transmission method, which suits especially the circumstances described with the aid of the example of Figure 2. The method is related to the admission control and load control procedures. The principle of the admission control is to check that the admittance of the new connection will not restrict the planned coverage area or make the quality of existing connection worse. The main target of the load control is to ensure that the system is not overloaded and remains stable. In this application, the term cell is used to mean both a radio cell and a sector.

In the method, terminals measure one or more values, which describe the level or the quality of the neighbouring cells pilots. These measurements can be utilized in the interference estimation. The radio network controller typically has information on the transmission powers of all the cells. It also has information on the quality of the pilot signals of all the cells, often called as $CPICH E_c/I_o$, that is to say Common Pilot Channel energy-to-noise-density, which are measured by terminals and reported periodically to radio network controllers. The terminals carry out these measurements particularly when they are about to perform a soft handover. The terminals report the neighbouring cell measurements to the radio network controller. These measurements can be, for instance, above-mentioned energy-to-noise-density ratio (E_c/I_o) measurements. Thus the radio network controller knows the total power in every cell.

In addition, it should be noticed that resource management, in other words resource allocations and releases, is the task of the radio network controller.

The embodiment of the method starts from block 400.

The method is especially beneficial in clarifying the influence of the expected power increase in one cell on the other cells. In a block 402 a maximum value is set for a cell power in each cell. The maximum value is preferably based on the limit for allowable interference caused by the cell for the other cells. Thus the maximum values can differ, for instance, in the function of time or they can be different for every cell. The adaptation of the method does not restrict the selection of the maximum values. If the cells are of the same size, the maximum values are typically set to be the same for all of the cells. With the aid of the method described here, the transmission powers can be controlled to be under the set limits or at least near them.

In block 404, the bit rate increases in the cells are determined. The current powers and bit rates used are known, and the increases are determined on the basis of the capacity requests. Typically, the increases are determined to all the cells belonging to the same radio network controller or the predetermined amount of cells. The capacity is needed for sending speech, packet data, picture etc. The increase of the bit rate depends on the amount of the requested connections as well as on their type; speech needs a lower bit rate than a picture, for example.

In block 406 the costs of the additional loads are evaluated. The total cost function is the sum of the interference increases of the other, typically adjacent, cells. The cost function is evaluated by using the formula

$$\Delta F(j) = (I + F_{tot}) \cdot \Delta P_s(j) / P_s(j), \quad (9)$$

where

F_{tot} is the same as in the equations (5) and (6),
 $\Delta P_s(j)$ is the increase of the transmission power in cell k,
 $P_s(j)$ is the current transmission power in cell k,
 j means the cell of interest.

The total cost is the sum of $\Delta F(j)$ calculated for all chosen cells. The purpose of evaluating the cost function is to define the effects of the power increase in a certain cell on other cells.

In block 408 the increase of the transmission power in the current cell caused by the capacity growth is estimated. The bit rate increase causes, of course, power increase. The power increase is preferably determined by using a derivative method, an integral method or both. The methods are explained previously in the description with the aid of formulas (1) and (2).

In block 410 the cell power of the current cell is determined on the basis of the current cell power and the estimated power increase. This is done preferably by adding the estimated power increase to the known current power.

5 In block 412 the increase of the transmission power needed in the other, typically neighbouring, cells due to the capacity increase is estimated. This process has already been depicted with the aid of formulas (3) to (8).

In block 414 the resources are allocated in the growing order of costs. This means that the cell with the smallest cost function is the first from
10 which the resources are reserved etc. This is done to ensure that the power increase is allocated to the cells, which cause least interference to other cells.

If the cell power of any of the neighbouring cells exceeds the maximum value, then the resource allocation in the cell requesting capacity is limited in order to avoid the interference level exceeding the boundary of the interference tolerance of the system in block 416. The resource allocation can be
15 restricted by offering lower bit rates or by limiting the number of new users.

The method can be repeated till there is no longer a cell which exceeds the upper limit of the maximum power. Pointer 420 represents this repeating process. The method ends in block 418.

20 Figure 5 shows a simplified example of a radio network controller (RNC) where the embodiments of the data transmission method can be accomplished. RNC is, as mentioned above, the switching and controlling element of UTRAN. UTRAN is the network element of the UMTS network. The switching unit 500 takes care of the connection between the core network and
25 the user equipment. The radio network controller is located between the Iub 502 and Iu 514 interfaces. There is also an interface for inter-RNC transmission called Iur 516. Blocks 504 and 512 depict the interface units between the radio network controller and other networks. The precise implementation of the radio network controller is producer specific.

30 The functionality of the radio network controller can be classified into two classes: UTRAN radio resource management 508 and control functions 506. An operation and management interface function 510 serves as a medium for information transfer to and from network management functions. The radio resource management is a group of algorithms used to share and
35 manage the radio path connection so that the quality and capacity of the connection are adequate. The most important radio resource management algo-

rithms are handover control, power control, admission control, packet scheduling, and code management. The UTRAN control functions take care of functions related to the set-up, maintenance and release of a radio connection between base stations and user equipment.

5 The radio network controller performs the actions needed in the handover. Most of them belong to the radio resource management functions. The information on the other cell, typically adjacent cell, pilots, for example the results of the energy-to-noise-density ratio (E_d/I_o) measurements, is in this example stored the memory belonging to the radio resource management func-
10 tions 518.

 The disclosed functionalities of the described embodiments of the data transmission method can be advantageously implemented by means of software located typically in the radio resource management block 508 of the radio network controller.

15 Even though the invention is described above with reference to an example according to the accompanying drawings, it is clear that the invention is not restricted thereto but it can be modified in several ways within the scope of the appended claims.

Claims

1. A data transmission method in a radio telecommunication system,
characterized by
setting (302) a maximum value for cell power,
5 determining (304) a bit rate increase in a cell on the basis of capacity requests,
estimating (306) the increase of the transmission power in a cell
caused by the capacity increase,
determining (308) the cell power on the basis of the current cell
10 power and the estimated power increase,
estimating (310) the increase of the transmission power needed in
the neighbouring cells caused by the capacity growth in the current cell,
if the cell power of any of the neighbouring cells exceeds the maximum value,
15 limiting (312) the resource allocation in the cell requesting capacity.
2. A data transmission method in a cellular telecommunication system,
characterized by
setting (402) a maximum value for a cell power,
20 determining (404) bit rate increases in cells on the basis of capacity requests,
evaluating (406) the costs of the additional loads due to the capacity requests,
estimating (408) the increase of the transmission power in the current cell caused by the capacity growth,
25 determining (410) the cell power of the current cell on the basis of the current cell power and the estimated power increase,
estimating (412) the increase of the transmission power needed in the neighbouring cells caused by the capacity growth in the current cell,
30 allocating (414) resources in a growing order of the costs,
if the cell power of any of the neighbouring cells exceeds the maximum value,
limiting (416) the resource allocation in the cell requesting capacity.
3. The method of claim 1 or 2, characterized by determining
35 a bit rate increase by the aid of the current power and the bit rate as well as the capacity requests.

4. The method of claim 1 or 2, characterized by estimating the increase of the transmission power by the derivative method.

5. The method of claim 1 or 2, characterized by estimating the increase of the transmission power by the integral method.

5 6. The method of claim 1 or 2, characterized by estimating the increase of the transmission power caused for the neighbouring cells using the formula $P_s'(j) = P_s(j)(1 + F_{tot}')/(1 + F_{tot})$.

7. The method of claim 2, characterized by evaluating the cost of the additional load using the formula $\Delta F(j) = (1 + F_{tot}) \cdot \Delta P_s(j) / P_s(j)$.

10 8. A radio telecommunication system characterized by comprising means (508) for determining a bit rate increase in a cell on the basis of capacity requests,

means (508) for estimating the increase of transmission power caused by the capacity increase,

15 means (508, 518) for determining the cell power on the basis of the current cell power and the estimated power increase,

means (508, 518) for estimating the increase of the transmission power needed in the neighbouring cells caused by the capacity growth in the current cell,

20 means (508) for limiting the resource allocation in the cell requesting capacity.

9. A radio telecommunication system characterized by comprising

25 means (508) for determining a bit rate increase in a cell on the basis of capacity requests,

means (508) for evaluating the cost of an additional load,

means (508, 518) for allocating resources in a growing order of costs,

30 means (508) for estimating the increase of transmission power caused by the capacity increase,

means (508, 518) for determining the cell power on the basis of the current cell power and the estimated power increase,

35 means (508, 518) for estimating the increase of the transmission power needed in the neighbouring cells caused by the capacity growth in the current cell,

means (508) for limiting the resource allocation in the cell requesting capacity.

10. The system of claim 8 or 9, characterized in that the system comprises means (508, 518) for determining a bit rate increase by the aid
5 of the current power and the bit rate as well as the capacity requests.

11. The system of claim 8 or 9, characterized in that the system comprises means (508, 518) for estimating the increase of the transmission power by the derivative method.

12. The system of claim 8 or 9, characterized in that the system
10 comprises means (508, 518) for estimating the increase of the transmission power by the integral method.

13. The system of claim 8 or 9, characterized in that the system comprises means (508, 518) for estimating the increase of the transmission power caused for the neighbouring cells using the formula
15 $P_s'(j) = P_s(j)(1 + F_{tot}')/(1 + F_{tot})$.

14. The system of claim 9, characterized in that the system comprises means (508, 518) for evaluating the cost of the additional load using the formula $\Delta F(j) = (1 + F_{tot}) \cdot \Delta P_s(j) / P_s(j)$.

(57) Abstract

The invention relates to a radio telecommunication system comprising means (508) for determining a bit rate increase in a cell on the basis of capacity requests, means (508) for estimating the increase of transmission power caused by the capacity increase, means (508, 518) for determining the cell power on the basis of the current cell power and the estimated power increase, means (508, 518) for estimating the increase of the transmission power needed in the neighbouring cells caused by the capacity growth in the current cell, means (508) for limiting the resource allocation in the cell requesting capacity.

(Figure 5)

1/4




Fig. 1




Fig. 2




Fig. 5

3/4




Fig. 3

4/4




Fig. 4